

# Stratos Pro

## A402 MSPH/MSPH

### Transmitter Specific HART Command Specification

Device Type 0xD0 (A402 MSPH/MSPH)

Device Revision: 2

Document Revision 1.3

**Knick Elektronische Messgeräte GmbH & Co. KG**

**www.knick.de**

HART is a registered trademark of the HART® Communication Foundation of Austin, Texas, USA.

#### 1 Reference Documents

| Document Title  | Revision | Document Number |
|---|----------|-----------------|
| HART® - FSK Physical Layer Specification                | 8.1      | HCF_SPEC-54     |
| HART® - Data Link Layer Specification                   | 8.0      | HCF_SPEC-81     |
| HART® - Command Summary Specification                   | 8.1      | HCF_SPEC-99     |
| HART® - Universal Command Specification                 | 6.0      | HCF_SPEC-127    |
| HART® - Common Practice Command Specification           | 8.0      | HCF_SPEC-151    |
| HART® - Common Tables                                   | 16.0     | HCF_SPEC-183    |
| Appendix 1 - Command Specific Response Code Definitions | 5.0      | HCF_SPEC-307    |
| Application Layer Guideline on HART Status Information  | 1.0      | HCF_LIT-5       |

# Content

|      |   |    |
|------|---|----|
| 1    | Reference Documents.....  | 1  |
| 2    | Common Tables Related to A402 MSPH/MSPH.....                    | 4  |
| 2.1  | Device Variable Code Tables.....                                | 4  |
| 2.2  | Analog Channel Code Table.....                                  | 4  |
| 3    | Universal Commands.....   | 5  |
| 3.1  | Command 0 Read Unique Identifier.....                           | 5  |
| 3.2  | Command 1 Read Primary Variable.....                            | 5  |
| 3.3  | Command 2 Read Loop Current and Percent of Range.....           | 6  |
| 3.4  | Command 3 Read Dynamic Variables and Loop Current.....          | 6  |
| 3.5  | Command 6 Write Polling Address.....                            | 7  |
| 3.6  | Command 7 Read Loop Configuration.....                          | 7  |
| 3.7  | Command 8 Read Dynamic Variable Classifications.....            | 8  |
| 3.8  | Command 9 Read Device Variables with Status.....                | 9  |
| 3.9  | Command 11 Read Unique Identifier Associated with Tag.....      | 10 |
| 3.10 | Command 12 Read Message.....                                    | 10 |
| 3.11 | Command 13 Read Tag, Descriptor, Date.....                      | 10 |
| 3.12 | Command 14 Read Primary Variable Transducer Information.....    | 11 |
| 3.13 | Command 15 Read Device Information.....                         | 11 |
| 3.14 | Command 16 Read Final Assembly Number.....                      | 12 |
| 3.15 | Command 17 Write Message.....                                   | 12 |
| 3.16 | Command 18 Write Tag, Descriptor, Date.....                     | 13 |
| 3.17 | Command 19 Write Final Assembly Number.....                     | 13 |
| 3.18 | Command 20 Read Long Tag.....                                   | 14 |
| 3.19 | Command 21 Read Unique Identifier Associated With Long Tag..... | 14 |
| 3.20 | Command 22 Write Long Tag.....                                  | 14 |
| 4    | Common Practice Commands.....                                   | 15 |
| 4.1  | Command 33 Read Device Variables.....                           | 15 |
| 4.2  | Command 35 Write Primary Variable Range Values.....             | 16 |
| 4.3  | Command 36 Set Primary Variable Upper Range Value.....          | 16 |
| 4.4  | Command 37 Set Primary Variable Lower Range Value.....          | 17 |
| 4.5  | Command 38 Reset Configuration Changed Flag.....                | 17 |
| 4.6  | Command 41 Perform Self Test.....                               | 18 |
| 4.7  | Command 42 Perform Device Reset.....                            | 18 |
| 4.8  | Command 44 Write Primary Variable Units.....                    | 18 |
| 4.9  | Command 47 Write Primary Variable Transfer Function.....        | 19 |
| 4.10 | Command 48 Read Additional Device Status.....                   | 20 |
| 4.11 | Command 50 Read Dynamic Variable Assignment.....                | 21 |
| 4.12 | Command 53 Write Device Variable Units.....                     | 21 |
| 4.13 | Command 54 Read Device Variable Information.....                | 22 |
| 4.14 | Command 59 Write Number of Response Preambles.....              | 22 |
| 4.15 | Command 60 Read Analog Channel and Percent of Range.....        | 23 |
| 4.16 | Command 62 Read Analog Channels.....                            | 23 |
| 4.17 | Command 63 Read Analog Channel Information.....                 | 24 |
| 4.18 | Command 64 Write Analog Channel Additional Damping Value.....   | 24 |
| 4.19 | Command 65 Write Analog Channel Range Values.....               | 25 |
| 4.20 | Command 69 Write Analog Channel Transfer Function.....          | 25 |
| 4.21 | Command 71 Lock Device.....                                     | 26 |
| 4.22 | Command 72 Squawk.....  | 26 |
| 4.23 | Command 73 Find Device.....                                     | 27 |
| 4.24 | Command 76 Read Lock Device State.....                          | 27 |
| 5    | Device Specific Commands.....                                   | 28 |
| 5.1  | Command 128 Read Device Configuration.....                      | 28 |
| 5.2  | Command 129 Read Sensor Information.....                        | 29 |
| 5.3  | Command 130 Write Sensor Information.....                       | 30 |
| 5.4  | Command 137 Read Meas Mode.....                                 | 30 |
| 5.5  | Command 138 Write Meas Mode.....                                | 31 |
| 5.6  | Command 141 Read OUT1/OUT2.....                                 | 32 |
| 5.7  | Command 142 Write OUT1/OUT2.....                                | 33 |

|      |             |   |    |
|------|-------------|---|----|
| 5.8  | Command 161 | Read Alarm.....   | 35 |
| 5.9  | Command 162 | Write Alarm.....  | 35 |
| 5.10 | Command 163 | Read Relais.....  | 36 |
| 5.11 | Command 164 | Write Relais.....   | 36 |
| 5.12 | Command 165 | Read Limits.....  | 37 |
| 5.13 | Command 166 | Write Limits.....   | 37 |
| 5.14 | Command 167 | Read Controller.....  | 38 |
| 5.15 | Command 168 | Write Controller.....                                       | 39 |
| 5.16 | Command 171 | Read Wash.....  | 40 |
| 5.17 | Command 172 | Write Wash.....   | 40 |
| 5.18 | Command 173 | Read Clock.....   | 41 |
| 5.19 | Command 174 | Write Clock.....  | 41 |
| 5.20 | Command 175 | Read Logbook Entry.....                                     | 42 |
| 5.21 | Command 176 | Store Actual Process Value.....                             | 43 |
| 5.22 | Command 177 | Read Stored Process Value.....                              | 43 |
| 5.23 | Command 178 | Write Calibration Reference Value.....                      | 44 |
| 5.24 | Command 179 | Read Slope and Zero Values.....                             | 44 |
| 5.25 | Command 183 | Read Device Tag.....  | 47 |
| 5.26 | Command 184 | Write Device Tag.....                                       | 47 |
| 5.27 | Command 185 | Read Sensor Identification.....                             | 48 |
| 5.28 | Command 186 | Read Unit Code.....   | 48 |
| 5.29 | Command 187 | Read Version Info.....                                      | 49 |
| 5.30 | Command 188 | Read Calibration Values.....                                | 49 |
| 5.31 | Command 189 | Read Process Values.....                                    | 51 |
| 5.32 | Command 190 | Read Digital Sensor Information.....                        | 52 |
| 5.33 | Command 191 | Read Last Calibration Date.....                             | 52 |
| 5.34 | Command 192 | Read User Specific Buffer Values.....                       | 53 |
| 5.35 | Command 193 | Write User Specific Buffer Values.....                      | 53 |
| 5.36 | Command 194 | Read User Specific Buffer Set Consistency Check Result..... | 54 |
| 5.37 | Command 195 | Write TV and QV Assignment.....                             | 54 |
| 5.38 | Command 196 | Read Product Calibration Success.....                       | 54 |

## 2 Common Tables Related to A402 MSPH/MSPH

### 2.1 Device Variable Code Tables

| Device Variable Code | Measurement Value      | Units Code | Lower Limit | Upper Limit | Minimum Span | Damping |
|----------------------|------------------------|------------|-------------|-------------|--------------|---------|
| 0                    | pH (Sensor A)          | 59 – pH    | -2          | 16          | 0,005        | 0       |
| 1                    | ORP (Sensor A)         | 36 – mV    | -1999       | 1999        | 0,5          | 0       |
| 2                    | Temperature (Sensor A) | 32 – °C    | -20         | 200         | 0,05         | 0       |
|                      |                        | 33 – °F    | -4          | 392         | 0,05         | 0       |
| 3                    | pH (Sensor B)          | 59 – pH    | -2          | 16          | 0,005        | 0       |
| 4                    | ORP (Sensor B)         | 36 – mV    | -1999       | 1999        | 0,5          | 0       |
| 5                    | Temperature (Sensor B) | 32 – °C    | -20         | 200         | 0,05         | 0       |
|                      |                        | 33 – °F    | -4          | 392         | 0,05         | 0       |
| 6                    | Diff pH (C1)           | 59 – pH    | -19,99      | 19,99       | 0,005        | 0       |
| 7                    | Diff ORP (C2)          | 36 – mV    | -1999       | 1999        | 0,5          | 0       |
| 8                    | Temperature (C3)       | 32 – °C    | -199,9      | 300         | 0,05         | 0       |
|                      |                        | 33 – °F    | -199,9      | 500         | 0,05         | 0       |

| Device Variable Code | Device Variable | Device Variable Class | Device Variable Family |
|----------------------|-----------------|-----------------------|------------------------|
| 0, 3, 6              | pH              | 81 – Analytical       | 8 – pH                 |
| 1, 4, 7              | ORP             | 81 – Analytical       | 250 – Not Used         |
| 2, 5, 8              | Temperature     | 64 – Temperature      | 4 – Temperature        |

### 2.2 Analog Channel Code Table

| Analog Channel Code | Current Loop of Device        |
|---------------------|-------------------------------|
| 0                   | Primary Current Loop (OUT1)   |
| 1                   | Secondary Current Loop (OUT2) |

### 3 Universal Commands

#### 3.1 Command 0 Read Unique Identifier

##### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| None |        |             |

##### Response Data Bytes

| Byte  | Format      | Description  |
|-------|-------------|--|
| 0     | Unsigned-8  | (=254)   |
| 1     | Enum        | Manufacturer Identification Code (=97, Knick)                          |
| 2     | Enum        | Device Type (=0xD0, A402 MSPH/MSPH)                                    |
| 3     | Unsigned-8  | Minimum Number of Preambles (=5)                                       |
| 4     | Unsigned-8  | Universal Command Major Revision Number (=6)                           |
| 5     | Unsigned-8  | Device Revision Level (=2)   |
| 6     | Unsigned-8  | Software Revision Level (=1)   |
| 7     | Enum        | Hardware Revision Level (=1)   |
| 8     | Bits        | Flags (=0)   |
| 9-11  | Unsigned-24 | Device Identification Number   |
| 12    | Unsigned-8  | Number of Preambles  |
| 13    | Unsigned-8  | Maximum Number of Device Variables (=8, Index of last device variable) |
| 14-15 | Unsigned-16 | Configuration Change Counter   |
| 16    | Bits        | Extended Field Device Status   |

##### Command-Specific Response Codes

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |

#### 3.2 Command 1 Read Primary Variable

##### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| None |        |             |

##### Response Data Bytes

| Byte | Format     | Description                                  |
|------|------------|--|
| 0    | Unsigned-8 | Primary Variable Units Code (Coding see 2.1) |
| 1-4  | Float      | Primary Variable                             |

##### Command-Specific Response Codes

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |

### 3.3 Command 2 Read Loop Current and Percent of Range

#### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| None |        |             |

#### Response Data Bytes

| Byte | Format | Description                           |
|------|--------|---------------------------------------|
| 0-3  | Float  | Primary Variable Loop Current [mA]    |
| 4-7  | Float  | Primary Variable Percent of Range [%] |

#### Command-Specific Response Codes

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |

### 3.4 Command 3 Read Dynamic Variables and Loop Current

#### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| None |        |             |

#### Response Data Bytes

| Byte  | Format | Description                                     |
|-------|--------|---|
| 0-3   | Float  | Primary Variable Loop Current [mA]              |
| 4     | Enum   | Primary Variable Units Code (Coding see 2.1)    |
| 5-8   | Float  | Primary Variable                                |
| 9     | Enum   | Secondary Variable Units Code (Coding see 2.1)  |
| 10-13 | Float  | Secondary Variable                              |
| 14    | Enum   | Tertiary Variable Units Code (Coding see 2.1)   |
| 15-18 | Float  | Tertiary Variable                               |
| 19    | Enum   | Quaternary Variable Units Code (Coding see 2.1) |
| 20-23 | Float  | Quaternary Variable                             |

#### Command-Specific Response Codes

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |

### 3.5 Command 6 Write Polling Address

#### Request Data Bytes

| Byte | Format     | Description  |
|------|------------|--|
| 0    | Unsigned-8 | Polling Address of Device  |
| 1    | Enum       | Loop Current Mode<br>0 – Disabled (= Multidrop Mode)<br>1 – Enabled (= Current Signaling Mode) |

#### Response Data Bytes

| Byte | Format     | Description               |
|------|------------|---------------------------|
| 0    | Unsigned-8 | Polling Address of Device |
| 1    | Enum       | Loop Current Mode         |

#### Command-Specific Response Codes

| Code | Class   | Description                             |
|------|---------|---|
| 0    | Success | No Command-Specific Errors              |
| 2    | Error   | Invalid Polling Address Selection (>63) |
| 5    | Error   | Too Few Data Bytes Received             |
| 16   | Error   | Access Restricted                       |

### 3.6 Command 7 Read Loop Configuration

#### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| None |        |             |

#### Response Data Bytes

| Byte | Format     | Description                              |
|------|------------|--|
| 0    | Unsigned-8 | Polling Address of Device                |
| 1    | Enum       | Loop Current Mode (Coding see Command 6) |

#### Command-Specific Response Codes

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |

### 3.7 Command 8 Read Dynamic Variable Classifications

#### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| None |        |             |

#### Response Data Bytes

| Byte | Format | Description   |
|------|--------|---|
| 0    | Enum   | Primary Variable Classification (Coding see 2.1)    |
| 1    | Enum   | Secondary Variable Classification (Coding see 2.1)  |
| 2    | Enum   | Tertiary Variable Classification (Coding see 2.1)   |
| 3    | Enum   | Quaternary Variable Classification (Coding see 2.1) |

#### Command-Specific Response Codes

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |



### 3.8 Command 9 Read Device Variables with Status

#### Request Data Bytes

| Byte | Format     | Description                                   |
|------|------------|---|
| 0    | Unsigned-8 | Slot 0: Device Variable Code (Coding see 2.1) |
| 1    | Unsigned-8 | Slot 1: Device Variable Code (Coding see 2.1) |
| 2    | Unsigned-8 | Slot 2: Device Variable Code (Coding see 2.1) |
| 3    | Unsigned-8 | Slot 3: Device Variable Code (Coding see 2.1) |

#### Response Data Bytes

| Byte  | Format     | Description   |
|-------|------------|---|
| 0     | Enum       | Extended Field Device Status  |
| 1     | Unsigned-8 | Slot 0: Device Variable Code (Coding see 2.1)   |
| 2     | Enum       | Slot 0: Device Variable Classification  |
| 3     | Enum       | Slot 0: Units Code  |
| 4-7   | Float      | Slot 0: Device Variable Value   |
| 8     | Bits       | Slot 0: Device Variable Status<br>0x80 – 0x40:<br>00 – Bad<br>01 – Poor<br>11 – Good<br>0x20 – 0x10:<br>00 - ok<br>01 - Low Limited<br>10 - High Limited<br>11 - Constant |
| 9     | Unsigned-8 | Slot 1: Device Variable Code  |
| 10    | Enum       | Slot 1: Device Variable Classification  |
| 11    | Enum       | Slot 1: Units Code  |
| 12-15 | Float      | Slot 1: Device Variable Value   |
| 16    | Bits       | Slot 1: Device Variable Status (Coding see Byte 8)  |
| 17    | Unsigned-8 | Slot 2: Device Variable Code  |
| 18    | Enum       | Slot 2: Device Variable Classification  |
| 19    | Enum       | Slot 2: Units Code  |
| 20-23 | Float      | Slot 2: Device Variable Value   |
| 24    | Bits       | Slot 2: Device Variable Status (Coding see Byte 8)  |
| 25    | Unsigned-8 | Slot 3: Device Variable Code  |
| 26    | Enum       | Slot 3: Device Variable Classification  |
| 27    | Enum       | Slot 3: Units Code  |
| 28-31 | Float      | Slot 3: Device Variable Value   |
| 32    | Bits       | Slot 3: Device Variable Status (Coding see Byte 8)  |

#### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 2    | Error   | Invalid Selection           |
| 5    | Error   | Too Few Data Bytes Received |
| 8    | Warning | Update Failure              |

### 3.9 Command 11 Read Unique Identifier Associated with Tag

#### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| 0-5  | Packed | Tag         |

#### Response Data Bytes

| Byte | Format | Description  |
|------|--------|--|
| 0-16 |        | Same as Command 0 (Read Unique Identifier)<br>No response is made unless the Tag matches that of the device. |

#### Command-Specific Response Codes

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |

### 3.10 Command 12 Read Message

#### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| None |        |             |

#### Response Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| 0-23 | Packed | Message     |

#### Command-Specific Response Codes

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |

### 3.11 Command 13 Read Tag, Descriptor, Date

#### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| None |        |             |

#### Response Data Bytes

| Byte  | Format | Description |
|-------|--------|-------------|
| 0-5   | Packed | Tag         |
| 6-17  | Packed | Descriptor  |
| 18-20 | Date   | Date Code   |

#### Command-Specific Response Codes

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |

### 3.12 Command 14 Read Primary Variable Transducer Information

#### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| None |        |             |

#### Response Data Bytes

| Byte  | Format      | Description  |
|-------|-------------|--|
| 0-2   | Unsigned-24 | Numerical Sensor Serialnumber - ISM sensors only (reads 0 if there is no ISM sensor) |
| 3     | Enum        | Transducer Limits and Minimum Span Units Code (Coding see 2.1)                       |
| 4-7   | Float       | Upper Transducer Limit   |
| 8-11  | Float       | Lower Transducer Limit   |
| 12-15 | Float       | Minimum Span   |

#### Command-Specific Response Codes

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |

### 3.13 Command 15 Read Device Information

#### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| None |        |             |

#### Response Data Bytes

| Byte  | Format | Description   |
|-------|--------|---|
| 0     | Enum   | PV Alarm Selection Code<br>0 – High<br>239 – Last Val       |
| 1     | Enum   | PV Transfer Function Code (=0, linear)                      |
| 2     | Enum   | PV Upper and Lower Range Values Units Code (Coding see 2.1) |
| 3-6   | Float  | PV Upper Range Value  |
| 7-10  | Float  | PV Lower Range Value  |
| 11-14 | Float  | PV Damping Value [s]  |
| 15    | Enum   | Write Protect Code (=251, None)                             |
| 16    | Enum   | Private Label Distributor Code (=97, Knick)                 |
| 17    | Bits   | PV Analog Channel Flags (=0)                                |

#### Command-Specific Response Codes

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |

### 3.14 Command 16 Read Final Assembly Number

#### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| None |        |             |

#### Response Data Bytes

| Byte | Format      | Description           |
|------|-------------|-----------------------|
| 0-2  | Unsigned-24 | Final Assembly Number |

#### Command-Specific Response Codes

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |

### 3.15 Command 17 Write Message

#### Request Data Bytes

| Byte | Format | Description  |
|------|--------|--|
| 0-23 | Packed | Message String Used by the Master for Record Keeping |

#### Response Data Bytes

| Byte | Format | Description    |
|------|--------|----------------|
| 0-23 | Packed | Message String |

#### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 5    | Error   | Too Few Data Bytes Received |
| 16   | Error   | Access Restricted           |

### 3.16 Command 18 Write Tag, Descriptor, Date

#### Request Data Bytes

| Byte  | Format      | Description  |
|-------|-------------|--|
| 0-5   | Packed      | Tag  |
| 6-17  | Packed      | Descriptor Used by the Master for Record Keeping                                       |
| 18-20 | Unsigned-24 | A Date Code Used by the Master for Record Keeping (e.g. Last Or Next Calibration Date) |

#### Response Data Bytes

| Byte  | Format | Description |
|-------|--------|-------------|
| 0-5   | Packed | Tag         |
| 6-17  | Packed | Descriptor  |
| 18-20 | Date   | Date Code   |

#### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 5    | Error   | Too Few Data Bytes Received |
| 9    | Error   | Invalid Date Code Detected  |
| 16   | Error   | Access Restricted           |

### 3.17 Command 19 Write Final Assembly Number

#### Request Data Bytes

| Byte | Format      | Description           |
|------|-------------|-----------------------|
| 0-2  | Unsigned-24 | Final Assembly Number |

#### Response Data Bytes

| Byte | Format      | Description           |
|------|-------------|-----------------------|
| 0-2  | Unsigned-24 | Final Assembly Number |

#### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 5    | Error   | Too Few Data Bytes Received |
| 16   | Error   | Access Restricted           |

### 3.18 Command 20 Read Long Tag

#### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| None |        |             |

#### Response Data Bytes

| Byte | Format  | Description |
|------|---------|-------------|
| 0-31 | Latin-1 | Long Tag    |

#### Command-Specific Response Codes

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |

### 3.19 Command 21 Read Unique Identifier Associated With Long Tag

#### Request Data Bytes

| Byte | Format  | Description |
|------|---------|-------------|
| 0-31 | Latin-1 | Long Tag    |

#### Response Data Bytes

| Byte | Format | Description   |
|------|--------|---|
| 0-16 |        | Same as Command 0 (Read Unique Identifier)<br>No response is made unless the Long Tag matches that of the device. |

#### Command-Specific Response Codes

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |

### 3.20 Command 22 Write Long Tag

#### Request Data Bytes

| Byte | Format  | Description |
|------|---------|-------------|
| 0-31 | Latin-1 | Long Tag    |

#### Response Data Bytes

| Byte | Format  | Description |
|------|---------|-------------|
| 0-31 | Latin-1 | Long Tag    |

#### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 5    | Error   | Too Few Data Bytes Received |
| 16   | Error   | Access Restricted           |

## 4 Common Practice Commands

### 4.1 Command 33 Read Device Variables

#### Request Data Bytes

| Byte | Format     | Description                                   |
|------|------------|---|
| 0    | Unsigned-8 | Slot 0: Device Variable Code (Coding see 2.1) |
| 1    | Unsigned-8 | Slot 1: Device Variable Code (Coding see 2.1) |
| 2    | Unsigned-8 | Slot 2: Device Variable Code (Coding see 2.1) |
| 3    | Unsigned-8 | Slot 3: Device Variable Code (Coding see 2.1) |

#### Response Data Bytes

| Byte  | Format     | Description                         |
|-------|------------|-------------------------------------|
| 0     | Unsigned-8 | Slot 0: Device Variable Code        |
| 1     | Enum       | Slot 0: Units Code (Coding see 2.1) |
| 2-5   | Float      | Slot 0: Device Variable Value       |
| 6     | Unsigned-8 | Slot 1: Device Variable Code        |
| 7     | Enum       | Slot 1: Units Code (Coding see 2.1) |
| 8-11  | Float      | Slot 1: Device Variable Value       |
| 12    | Unsigned-8 | Slot 2: Device Variable Code        |
| 13    | Enum       | Slot 2: Units Code (Coding see 2.1) |
| 14-17 | Float      | Slot 2: Device Variable Value       |
| 18    | Unsigned-8 | Slot 3: Device Variable Code        |
| 19    | Enum       | Slot 3: Units Code (Coding see 2.1) |
| 20-23 | Float      | Slot 3: Device Variable Value       |

#### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 2    | Error   | Invalid Selection           |
| 5    | Error   | Too Few Data Bytes Received |
| 8    | Warning | Update Failure              |

## 4.2 Command 35 Write Primary Variable Range Values

### Request Data Bytes

| Byte | Format     | Description   |
|------|------------|---|
| 0    | Unsigned-8 | Upper and Lower Range Values Units Code (must be the same as the actually used unit) (Coding see 2.1) |
| 1-4  | Float      | Upper Range Value   |
| 5-8  | Float      | Lower Range Value   |

### Response Data Bytes

| Byte | Format     | Description                             |
|------|------------|---|
| 0    | Unsigned-8 | Upper and Lower Range Values Units Code |
| 1-4  | Float      | Upper Range Value                       |
| 5-8  | Float      | Lower Range Value                       |

### Command-Specific Response Codes

| Code | Class   | Description                   |
|------|---------|-------------------------------|
| 0    | Success | No Command-Specific Errors    |
| 2    | Error   | Invalid Selection             |
| 5    | Error   | Too Few Data Bytes Received   |
| 6    | Error   | Device-Specific Command Error |
| 9    | Error   | Lower Range Value Too High    |
| 10   | Error   | Lower Range Value Too Low     |
| 11   | Error   | Upper Range Value Too High    |
| 12   | Error   | Upper Range Value Too Low     |
| 16   | Error   | Access Restricted             |
| 29   | Error   | Invalid Span                  |

## 4.3 Command 36 Set Primary Variable Upper Range Value

This Command sets the actual value of the Primary Variable as the Upper Range Value.

### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| None |        |             |

### Response Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| None |        |             |

### Command-Specific Response Codes

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |
| 9    | Error   | Applied Process Too High   |
| 10   | Error   | Applied Process Too Low    |
| 16   | Error   | Access Restricted          |
| 29   | Error   | Invalid Span               |



#### 4.4 Command 37 Set Primary Variable Lower Range Value

This Command sets the actual value of the Primary Variable as the Lower Range Value.

##### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| None |        |             |

##### Response Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| None |        |             |

##### Command-Specific Response Codes

| Code | Class   | Description                  |
|------|---------|------------------------------|
| 0    | Success | No Command-Specific Errors   |
| 9    | Error   | Applied Process Too High     |
| 10   | Error   | Applied Process Too Low      |
| 14   | Warning | New Lower Range Value Pushed |
| 16   | Error   | Access Restricted            |
| 29   | Error   | Invalid Span                 |

#### 4.5 Command 38 Reset Configuration Changed Flag

##### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| None |        |             |

##### Response Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| None |        |             |

##### Command-Specific Response Codes

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |
| 16   | Error   | Access Restricted          |

#### 4.6 Command 41 Perform Self Test

##### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| None |        |             |

##### Response Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| None |        |             |

##### Command-Specific Response Codes

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |
| 16   | Error   | Access Restricted          |

#### 4.7 Command 42 Perform Device Reset

##### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| None |        |             |

##### Response Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| None |        |             |

##### Command-Specific Response Codes

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |
| 16   | Error   | Access Restricted          |

#### 4.8 Command 44 Write Primary Variable Units

##### Request Data Bytes

| Byte | Format | Description  |
|------|--------|--|
| 0    | Enum   | Primary Variable Units Code (switching between °C and °F is allowed; pH and mV must not be changed) (Coding see 2.1) |

##### Response Data Bytes

| Byte | Format | Description                 |
|------|--------|-----------------------------|
| 0    | Enum   | Primary Variable Units Code |

##### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 2    | Error   | Invalid Selection           |
| 5    | Error   | Too Few Data Bytes Received |
| 16   | Error   | Access Restricted           |

#### 4.9 Command 47 Write Primary Variable Transfer Function

##### Request Data Bytes

| Byte | Format | Description                         |
|------|--------|-------------------------------------|
| 0    | Enum   | Transfer Function Code (=0, linear) |

##### Response Data Bytes

| Byte | Format | Description            |
|------|--------|------------------------|
| 0    | Enum   | Transfer Function Code |

##### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 2    | Error   | Invalid Selection           |
| 5    | Error   | Too Few Data Bytes Received |
| 16   | Error   | Access Restricted           |

#### 4.10 Command 48 Read Additional Device Status

##### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| None |        |             |

##### Response Data Bytes

| Byte  | Format     | Description   |
|-------|------------|---|
| 0     | Unsigned-8 | Error number  |
| 1     | Unsigned-8 | Reserved  |
| 2     | Enum       | Device Specific Status:<br>0 – MEAS<br>1 – DIAG<br>2 – CAL<br>3 – CONF<br>4 – SERVICE   |
| 3     | Enum       | Sensoface:<br>0x02-0x01: Sensor A and B together (like shown on device display)<br>0x08-0x04: Sensor A<br>0x20-0x10: Sensor B<br><br>Coding:<br>0 – Good<br>1 – Poor<br>2 – Bad<br>3 – Unknown                                    |
| 4     | Enum       | Reserved  |
| 5     | Bits       | State:<br>0x20 – Alarm<br>0x10 – Sensor Connected (Sensor B)<br>0x08 – Sensor Connected (Sensor A)<br>0x04 – Product Calibration Step 2 Pending (Sensor B)<br>0x02 – Product Calibration Step 2 Pending (Sensor A)<br>0x01 – Hold |
| 6     | Bits       | Extended Device Status:<br>0x01 – Maintenance required  |
| 7-9   | Bits       | Reserved  |
| 10    | Bits       | Analog Channel Saturation:<br>0x02 – Channel 2 saturated<br>0x01 – Channel 1 saturated  |
| 11-12 | Bits       | Reserved  |
| 13    | Bits       | Analog Channel Fixed:<br>0x02 – Channel 2 fixed<br>0x01 – Channel 1 fixed   |

##### Command-Specific Response Codes

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |

#### 4.11 Command 50 Read Dynamic Variable Assignment

##### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| None |        |             |

##### Response Data Bytes

| Byte | Format     | Description  |
|------|------------|--|
| 0    | Unsigned-8 | Device Variable assigned to the Primary Variable (Coding see 2.1)    |
| 1    | Unsigned-8 | Device Variable assigned to the Secondary Variable (Coding see 2.1)  |
| 2    | Unsigned-8 | Device Variable assigned to the Tertiary Variable (Coding see 2.1)   |
| 3    | Unsigned-8 | Device Variable assigned to the Quaternary Variable (Coding see 2.1) |

##### Command-Specific Response Codes

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |

#### 4.12 Command 53 Write Device Variable Units

##### Request Data Bytes

| Byte | Format     | Description  |
|------|------------|--|
| 0    | Unsigned-8 | Device Variable Code (Coding see 2.1)  |
| 1    | Enum       | Device Variable Units Code (switching between °C and °F is allowed; pH and mV must remain the same) (Coding see 2.1) |

##### Response Data Bytes

| Byte | Format     | Description                |
|------|------------|----------------------------|
| 0    | Unsigned-8 | Device Variable Code       |
| 1    | Enum       | Device Variable Units Code |

##### Command-Specific Response Codes

| Code | Class   | Description                  |
|------|---------|------------------------------|
| 0    | Success | No Command-Specific Errors   |
| 5    | Error   | Too Few Data Bytes Received  |
| 11   | Error   | Invalid Device Variable Code |
| 12   | Error   | Invalid Units Code           |
| 16   | Error   | Access Restricted            |

#### 4.13 Command 54 Read Device Variable Information

##### Request Data Bytes

| Byte | Format     | Description                           |
|------|------------|---------------------------------------|
| 0    | Unsigned-8 | Device Variable Code (Coding see 2.1) |

##### Response Data Bytes

| Byte  | Format      | Description   |
|-------|-------------|---|
| 0     | Unsigned-8  | Device Variable Code  |
| 1-3   | Unsigned-24 | Device Variable Transducer Serialnumber (ISM sensors only)      |
| 4     | Enum        | Device Variable Limits/Minimum Span Units Code (Coding see 2.1) |
| 5-8   | Float       | Device Variable Upper Transducer Limit                          |
| 9-12  | Float       | Device Variable Lower Transducer Limit                          |
| 13-16 | Float       | Device Variable Damping Value (=0)                              |
| 17-20 | Float       | Device Variable Minimum Span                                    |
| 21    | Enum        | Device Variable Classification (Coding see 2.1)                 |
| 22    | Enum        | Device Variable Family (Coding see 2.1)                         |

##### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 2    | Error   | Invalid Selection           |
| 5    | Error   | Too Few Data Bytes Received |

#### 4.14 Command 59 Write Number of Response Preambles

##### Request Data Bytes

| Byte | Format     | Description   |
|------|------------|---|
| 0    | Unsigned-8 | Number of preambles to be sent with the response message from Slave to the Master |

##### Response Data Bytes

| Byte | Format     | Description   |
|------|------------|---|
| 0    | Unsigned-8 | Number of preambles to be sent with the response message from Slave to the Master |

##### Command-Specific Response Codes

| Code | Class   | Description                   |
|------|---------|-------------------------------|
| 0    | Success | No Command-Specific Errors    |
| 5    | Error   | Too Few Data Bytes Received   |
| 8    | Warning | Set to Nearest Possible Value |
| 16   | Error   | Access Restricted             |

#### 4.15 Command 60 Read Analog Channel and Percent of Range

##### Request Data Bytes

| Byte | Format     | Description                                 |
|------|------------|---|
| 0    | Unsigned-8 | Analog Channel Number Code (Coding see 2.2) |

##### Response Data Bytes

| Byte | Format     | Description                         |
|------|------------|-------------------------------------|
| 0    | Unsigned-8 | Analog Channel Number Code          |
| 1    | Enum       | Analog Channel Units Code (=39, mA) |
| 2-5  | Float      | Analog Channel Level                |
| 6-9  | Float      | Analog Channel Percent of Range     |

##### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 2    | Error   | Invalid Selection           |
| 5    | Error   | Too Few Data Bytes Received |

#### 4.16 Command 62 Read Analog Channels

##### Request Data Bytes

| Byte | Format     | Description  |
|------|------------|--|
| 0    | Unsigned-8 | Analog Channel Number Code assigned to Slot 0 (Coding see 2.2) |
| 1    | Unsigned-8 | Analog Channel Number Code assigned to Slot 1 (Coding see 2.2) |
| 2    | Unsigned-8 | Analog Channel Number Code assigned to Slot 2 (Coding see 2.2) |
| 3    | Unsigned-8 | Analog Channel Number Code assigned to Slot 3 (Coding see 2.2) |

##### Response Data Bytes

| Byte  | Format     | Description                             |
|-------|------------|---|
| 0     | Unsigned-8 | Analog Channel Number Code in Slot 0    |
| 1     | Enum       | Slot 0 Units Code (=39, mA)             |
| 2-5   | Float      | Slot 0 Level of selected Analog Channel |
| 6     | Unsigned-8 | Analog Channel Number Code in Slot 1    |
| 7     | Enum       | Slot 1 Units Code (=39, mA)             |
| 8-11  | Float      | Slot 1 Level of selected Analog Channel |
| 12    | Unsigned-8 | Analog Channel Number Code in Slot 2    |
| 13    | Enum       | Slot 2 Units Code (=39, mA)             |
| 14-17 | Float      | Slot 2 Level of selected Analog Channel |
| 18    | Unsigned-8 | Analog Channel Number Code in Slot 3    |
| 19    | Enum       | Slot 3 Units Code (=39, mA)             |
| 20-23 | Float      | Slot 3 Level of selected Analog Channel |

##### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 2    | Error   | Invalid Selection           |
| 5    | Error   | Too Few Data Bytes Received |

#### 4.17 Command 63 Read Analog Channel Information

##### Request Data Bytes

| Byte | Format     | Description                                 |
|------|------------|---|
| 0    | Unsigned-8 | Analog Channel Number Code (Coding see 2.2) |

##### Response Data Bytes

| Byte  | Format     | Description   |
|-------|------------|---|
| 0     | Unsigned-8 | Analog Channel Number Code  |
| 1     | Enum       | Analog Channel Alarm Selection Code<br>0 – High<br>239 – Last Val       |
| 2     | Enum       | Analog Channel Transfer Function Code (=0, linear)                      |
| 3     | Enum       | Analog Channel Upper and Lower Range Values Units Code (Coding see 2.1) |
| 4-7   | Float      | Analog Channel Upper Range Value  |
| 8-11  | Float      | Analog Channel Lower Range Value  |
| 12-15 | Float      | Analog Channel Damping Value [s]  |
| 16    | Bits       | Analog Channel Flags (=0)   |

##### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 2    | Error   | Invalid Selection           |
| 5    | Error   | Too Few Data Bytes Received |

#### 4.18 Command 64 Write Analog Channel Additional Damping Value

##### Request Data Bytes

| Byte | Format     | Description                                 |
|------|------------|---|
| 0    | Unsigned-8 | Analog Channel Number Code (Coding see 2.2) |
| 1-4  | Float      | Analog Channel Additional Damping Value [s] |

##### Response Data Bytes

| Byte | Format     | Description                                 |
|------|------------|---|
| 0    | Unsigned-8 | Analog Channel Number Code                  |
| 6-9  | Float      | Analog Channel Additional Damping Value [s] |

##### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 2    | Error   | Invalid Selection           |
| 3    | Error   | Passed Parameter Too Large  |
| 4    | Error   | Passed Parameter Too Small  |
| 5    | Error   | Too Few Data Bytes Received |
| 16   | Error   | Access Restricted           |



#### 4.19 Command 65 Write Analog Channel Range Values

##### Request Data Bytes

| Byte | Format     | Description   |
|------|------------|---|
| 0    | Unsigned-8 | Analog Channel Number Code (Coding see 2.2)   |
| 1    | Enum       | Analog Channel Upper and Lower Range Values Units Codes (the actually used unit must not be changed) (Coding see 2.1) |
| 2-5  | Float      | Analog Channel Upper Range Value  |
| 6-9  | Float      | Analog Channel Lower Range Value  |

##### Response Data Bytes

| Byte | Format     | Description   |
|------|------------|---|
| 0    | Unsigned-8 | Analog Channel Number Code                              |
| 1    | Enum       | Analog Channel Upper and Lower Range Values Units Codes |
| 2-5  | Float      | Analog Channel Upper Range Value                        |
| 6-9  | Float      | Analog Channel Lower Range Value                        |

##### Command-Specific Response Codes

| Code | Class   | Description                        |
|------|---------|------------------------------------|
| 0    | Success | No Command-Specific Errors         |
| 2    | Error   | Invalid Selection                  |
| 5    | Error   | Too Few Data Bytes Received        |
| 6    | Error   | Device-Specific Error Code         |
| 9    | Error   | Lower Range Value Too High         |
| 10   | Error   | Lower Range Value Too Low          |
| 11   | Error   | Upper Range Value Too High         |
| 12   | Error   | Upper Range Value Too Low          |
| 15   | Error   | Invalid Analog Channel Code Number |
| 16   | Error   | Access Restricted                  |
| 29   | Error   | Invalid Span                       |

#### 4.20 Command 69 Write Analog Channel Transfer Function

##### Request Data Bytes

| Byte | Format     | Description  |
|------|------------|--|
| 0    | Unsigned-8 | Analog Channel Number Code (Coding see 2.2)        |
| 1    | Enum       | Analog Channel Transfer Function Code (=0, linear) |

##### Response Data Bytes

| Byte | Format     | Description                           |
|------|------------|---------------------------------------|
| 0    | Unsigned-8 | Analog Channel Number Code            |
| 1    | Enum       | Analog Channel Transfer Function Code |

##### Command-Specific Response Codes

| Code | Class   | Description                        |
|------|---------|------------------------------------|
| 0    | Success | No Command-Specific Errors         |
| 5    | Error   | Too Few Data Bytes Received        |
| 13   | Error   | Invalid Transfer Function Code     |
| 15   | Error   | Invalid Analog Channel Code Number |
| 16   | Error   | Access Restricted                  |

#### 4.21 Command 71 Lock Device

##### Request Data Bytes

| Byte | Format | Description  |
|------|--------|--|
| 0    | Enum   | Lock Code:<br>0 – Unlocked<br>1 – Lock – Temporary<br>2 – Lock – Permanent |

##### Response Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| 0    | Enum   | Lock Code   |

##### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 5    | Error   | Too Few Data Bytes Received |
| 10   | Error   | Invalid Lock Code           |
| 16   | Error   | Access Restricted           |

#### 4.22 Command 72 Squawk

##### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| None |        |             |

##### Response Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| None |        |             |

##### Command-Specific Response Codes

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |

#### 4.23 Command 73 Find Device

The A402 MSPH/MSPH must be set to Diag mode manually before using this command. In all other modes the device will not answer this command.

##### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| None |        |             |

##### Response Data Bytes

| Byte | Format | Description                                |
|------|--------|--|
| 0-16 | Bits   | Same as Command 0 (Read Unique Identifier) |

##### Command-Specific Response Codes

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |

#### 4.24 Command 76 Read Lock Device State

##### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| None |        |             |

##### Response Data Bytes

| Byte | Format | Description   |
|------|--------|---|
| 0    | Bits   | Lock Status:<br>0x01 – Device Locked<br>0x02 – Lock is Permanent<br>0x04 – Locked by Primary Master |

##### Command-Specific Response Codes

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |

## 5 Device Specific Commands

### 5.1 Command 128 Read Device Configuration

#### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| None |        |             |

#### Response Data Bytes

| Byte | Format     | Description  |
|------|------------|--|
| 0    | Bits       | Device type and options 1:<br>0x01 – reserved<br>0x02 – reserved<br>0x04 – 0 = non Ex, 1=Ex<br>0x08 – reserved<br>0x10 – reserved<br>0x20 – 1= option Logbook activated<br>0x40 – 1= option Current Input activated<br>0x80 – reserved |
| 1    | Bits       | Device type and options 2:<br>0x01 – 1 = option Audit Trail activated<br>0x02 – 0x80 – reserved  |
| 2    | Unsigned-8 | Reserved   |
| 3    | Unsigned-8 | Reserved   |

#### Command-Specific Response Codes

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |

## 5.2 Command 129 Read Sensor Information

### Request Data Bytes

| Byte | Format | Description                                       |
|------|--------|---|
| 0    | Enum   | Sensor Selection:<br>0 – Sensor A<br>1 – Sensor B |

### Response Data Bytes

| Byte | Format | Description   | Parameter Name on Display |
|------|--------|---|---------------------------|
| 0    | Enum   | Sensor Selection (Coding see Request)   |                           |
| 1    | Enum   | Sensor Activation:<br>0 – OFF<br>1 – ON   | S_A/B: SENSOR             |
| 2    | Enum   | Calibration Mode:<br>0 – AUTO<br>1 – MAN<br>2 – DAT   | S_A/B: CALMODE            |
| 3    | Enum   | Buffer Set:<br>1 – METTLER<br>2 – KNICK CALIMAT<br>3 – CIBA<br>4 – NIST TECH<br>5 – NIST STD<br>6 – HACH<br>7 – WTW<br>8 – HAMILTON<br>9 – REAGECON<br>10 – DIN<br>11 – USER SPECIFIC | S_A/B: BUFFER SET         |
| 4    | Enum   | CAL Timer:<br>0 – OFF<br>1 – FIX<br>2 – ADAPT   | S_A/B: CALTIMER           |
| 5-8  | Float  | CAL Cycle [h]   | S_A/B: CAL CYCLE          |
| 9-12 | Float  | TC Liquid [%/K]   | S_A/B: TC LIQUID          |
| 13   | Enum   | CIP Count:<br>0 – OFF<br>1 – ON   | S_A/B: CIP COUNT          |
| 14   | Enum   | SIP Count:<br>0 – OFF<br>1 – ON   | S_A/B: SIP COUNT          |

**Command-Specific Response Codes**

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 2    | Error   | Invalid Selection           |
| 5    | Error   | Too Few Data Bytes Received |

**5.3 Command 130 Write Sensor Information**

**Request Data Bytes**

| Byte | Format | Description                     |
|------|--------|---------------------------------|
| 0-14 |        | Same as Response of Command 129 |

**Response Data Bytes**

| Byte | Format | Description                     |
|------|--------|---------------------------------|
| 0-14 |        | Same as Response of Command 129 |

**Command-Specific Response Codes**

| Code | Class   | Description                   |
|------|---------|-------------------------------|
| 0    | Success | No Command-Specific Errors    |
| 2    | Error   | Invalid Selection             |
| 3    | Error   | Passed Parameter Too Large    |
| 4    | Error   | Passed Parameter Too Small    |
| 5    | Error   | Too Few Data Bytes Received   |
| 6    | Error   | Device-Specific Command Error |
| 16   | Error   | Access Restricted             |

**5.4 Command 137 Read Meas Mode**

**Request Data Bytes**

| Byte | Format | Description |
|------|--------|-------------|
| 0    | Enum   | (=0)        |

**Response Data Bytes**

| Byte | Format | Description  | Parameter Name on Display |
|------|--------|--|---------------------------|
| 0    | Enum   | (=0)   |                           |
| 1    | Enum   | Temperature Units Code:<br>32 – °C<br>33 – °F  | MES: TEMP UNIT            |
| 2    | Enum   | Calculation:<br>0 – OFF<br>1 – ON  | MES:CALCULATION           |
| 3    | Enum   | Calculation Type:<br>0 – Difference pH<br>1 – Difference ORP<br>2 – Difference Temperature | MES:DIFFERENCE            |

**Command-Specific Response Codes**

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |
| 2    | Error   | Invalid Selection          |

|   |       |                             |
|---|-------|-----------------------------|
| 5 | Error | Too Few Data Bytes Received |
|---|-------|-----------------------------|

## 5.5 Command 138 Write Meas Mode

### Request Data Bytes

| Byte | Format | Description                     |
|------|--------|---------------------------------|
| 0-3  |        | Same as Response of Command 137 |

### Response Data Bytes

| Byte | Format | Description                     |
|------|--------|---------------------------------|
| 0-3  |        | Same as Response of Command 137 |

### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 2    | Error   | Invalid Selection           |
| 5    | Error   | Too Few Data Bytes Received |
| 16   | Error   | Access Restricted           |

## 5.6 Command 141 Read OUT1/OUT2

### Request Data Bytes

| Byte | Format | Description                                       |
|------|--------|---|
| 0    | Enum   | Analog Channel Selection:<br>0 – OUT1<br>1 – OUT2 |

### Response Data Bytes

| Byte  | Format | Description   | Parameter Name on Display |
|-------|--------|---|---------------------------|
| 0     | Enum   | Analog Channel Selection (Coding see Request)   |                           |
| 1     | Enum   | Channel:<br>0 – PH A<br>1 – ORP A<br>2 – Temperature A<br>3 – PH B<br>4 – ORP B<br>5 – Temperature B<br>6 – Calculation | OT1/2: CHANNEL            |
| 2     | Enum   | Output Range:<br>0 – 0-20mA<br>1 – 4-20mA   | OT1/2: RANGE              |
| 3-6   | Float  | BEGIN Value   | OT1/2: BEGIN              |
| 7-10  | Float  | END Value   | OT1/2: END                |
| 11-14 | Float  | Filtertime [s]  | OT1/2: FILTERTIME         |
| 15    | Enum   | 22mA-Fail:<br>0 – OFF<br>1 – ON   | OT1/2: 22mA-FAIL          |
| 16    | Enum   | Hold Mode:<br>1 – FIX<br>3 – LAST   | OT1/2: HOLD MODE          |
| 17-20 | Float  | Hold Fix Value  | OT1/2: HOLD FIX           |
| 21    | Enum   | 22mA on Sensoface Message:<br>0 – OFF<br>1 – ON   | OT1/2: FACE 22mA          |

### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 2    | Error   | Invalid Selection           |
| 5    | Error   | Too Few Data Bytes Received |



## 5.7 Command 142 Write OUT1/OUT2

### Request Data Bytes

| Byte | Format | Description                     |
|------|--------|---------------------------------|
| 0-21 |        | Same as Response of Command 141 |

### Response Data Bytes

| Byte | Format | Description                     |
|------|--------|---------------------------------|
| 0-21 |        | Same as Response of Command 141 |

### Command-Specific Response Codes

| Code | Class   | Description                   |
|------|---------|-------------------------------|
| 0    | Success | No Command-Specific Errors    |
| 2    | Error   | Invalid Selection             |
| 3    | Error   | Passed Parameter Too Large    |
| 4    | Error   | Passed Parameter Too Small    |
| 5    | Error   | Too Few Data Bytes Received   |
| 6    | Error   | Device-Specific Command Error |
| 16   | Error   | Access Restricted             |



## 5.8 Command 161 Read Alarm

### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| 0    | Enum   | (=0)        |

### Response Data Bytes

| Byte  | Format | Description                                  | Parameter Name on Display |
|-------|--------|--|---------------------------|
| 0     | Enum   | (=0)   |                           |
| 1-4   | Float  | Delay Time [s]                               | ALA: DELAYTIME            |
| 5     | Enum   | Sensocheck:<br>0 – OFF<br>1 – ON             | ALA: SENSOCHECK           |
| 6     | Enum   | Control Input:<br>0 – OFF<br>1 – ON          | ALA: CONTROL IN           |
| 7     | Enum   | Limit I-Input<br>0 – OFF<br>1 – ON           | ALA: LIMIT I-IN           |
| 8     | Enum   | Function:<br>0 – Low Level<br>1 – High Level | ALA: FUNCTION             |
| 9-12  | Float  | Level [mA]                                   | ALA: LEVEL                |
| 13-16 | Float  | Hysteresis [mA]                              | ALA: HYSTERESIS           |

### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 2    | Error   | Invalid Selection           |
| 5    | Error   | Too Few Data Bytes Received |

## 5.9 Command 162 Write Alarm

### Request Data Bytes

| Byte | Format | Description                     |
|------|--------|---------------------------------|
| 0-16 |        | Same as Response of Command 161 |

### Response Data Bytes

| Byte | Format | Description                     |
|------|--------|---------------------------------|
| 0-16 |        | Same as Response of Command 161 |

### Command-Specific Response Codes

| Code | Class   | Description                   |
|------|---------|-------------------------------|
| 0    | Success | No Command-Specific Errors    |
| 2    | Error   | Invalid Selection             |
| 3    | Error   | Passed Parameter Too Large    |
| 4    | Error   | Passed Parameter Too Small    |
| 5    | Error   | Too Few Data Bytes Received   |
| 6    | Error   | Device-Specific Command Error |
| 16   | Error   | Access Restricted             |

### 5.10 Command 163 Read Relais

#### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| 0    | Enum   | (=0)        |

#### Response Data Bytes

| Byte | Format | Description                                  | Parameter Name on Display |
|------|--------|--|---------------------------|
| 0    | Enum   | (=0)   |                           |
| 1    | Enum   | Relais Mode:<br>0 – Limits<br>1 – Controller | REL:                      |

#### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 2    | Error   | Invalid Selection           |
| 5    | Error   | Too Few Data Bytes Received |

### 5.11 Command 164 Write Relais

#### Request Data Bytes

| Byte | Format | Description                     |
|------|--------|---------------------------------|
| 0-1  |        | Same as Response of Command 163 |

#### Response Data Bytes

| Byte | Format | Description                     |
|------|--------|---------------------------------|
| 0-1  |        | Same as Response of Command 163 |

#### Command-Specific Response Codes

| Code | Class   | Description                   |
|------|---------|-------------------------------|
| 0    | Success | No Command-Specific Errors    |
| 2    | Error   | Invalid Selection             |
| 5    | Error   | Too Few Data Bytes Received   |
| 6    | Error   | Device-Specific Command Error |
| 16   | Error   | Access Restricted             |

## 5.12 Command 165 Read Limits

### Request Data Bytes

| Byte | Format | Description                               |
|------|--------|---|
| 0    | Enum   | Relais Selection:<br>0 – Rel1<br>1 – Rel2 |

### Response Data Bytes

| Byte  | Format | Description   | Parameter Name on Display |
|-------|--------|---|---------------------------|
| 0     | Enum   | Relais Selection (Coding see Request)   |                           |
| 1     | Enum   | Channel:<br>0 – PH A<br>1 – ORP A<br>2 – Temperature (TMP) A<br>3 – PH B<br>4 – ORP B<br>5 – Temperature (TMP) B<br>6 – Calculation | RL1/2: CHANNEL            |
| 2     | Enum   | Function:<br>0 – Low Level<br>1 – High Level  | RL1/2: FUNCTION           |
| 3     | Enum   | Contact Type:<br>0 – N/O<br>1 – N/C   | RL1/2: CONTACT            |
| 4-7   | Float  | Level   | RL1/2: LEVEL              |
| 8-11  | Float  | Hysteresis  | RL1/2: HYSTERESIS         |
| 12-15 | Float  | Delay Time [s]  | RL1/2: DELAYTIME          |

### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 2    | Error   | Invalid Selection           |
| 5    | Error   | Too Few Data Bytes Received |

## 5.13 Command 166 Write Limits

### Request Data Bytes

| Byte | Format | Description                     |
|------|--------|---------------------------------|
| 0-15 |        | Same as Response of Command 165 |

### Response Data Bytes

| Byte | Format | Description                     |
|------|--------|---------------------------------|
| 0-15 |        | Same as Response of Command 165 |

### Command-Specific Response Codes

| Code | Class   | Description                   |
|------|---------|-------------------------------|
| 0    | Success | No Command-Specific Errors    |
| 2    | Error   | Invalid Selection             |
| 3    | Error   | Passed Parameter Too Large    |
| 4    | Error   | Passed Parameter Too Small    |
| 5    | Error   | Too Few Data Bytes Received   |
| 6    | Error   | Device-Specific Command Error |
| 16   | Error   | Access Restricted             |

## 5.14 Command 167 Read Controller

### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
| 0    | Enum   | (=0)        |

### Response Data Bytes

| Byte  | Format | Description  | Parameter Name on Display |
|-------|--------|--|---------------------------|
| 0     | Enum   | (=0)   |                           |
| 1     | Enum   | Channel:<br>0 – PH A<br>1 – ORP A<br>2 – Temperature (TMP) A<br>3 – PH B<br>4 – ORP B<br>5 – Temperature (TMP) B | CTR: CHANNEL              |
| 2     | Enum   | Controller Type:<br>0 – Pulse Length (PLC)<br>1 – Pulse Frequency (PFC)  | CTR: TYPE                 |
| 3-6   | Float  | Pulse Length [s]   | CTR: PULSE LEN            |
| 7-10  | Float  | Pulse Frequency [1/min]  | CTR: PULSE FREQ           |
| 11-14 | Float  | Set Point  | CTR: SETPOINT             |
| 15-18 | Float  | Dead Band  | CTR: DEAD BAND            |
| 19-22 | Float  | P Gain [%]   | CTR: P-GAIN               |
| 23-26 | Float  | I Time [s]   | CTR: I-TIME               |
| 27-30 | Float  | D Time [s]   | CTR: D-TIME               |
| 31    | Enum   | Hold Mode:<br>0 – Y OFF<br>3 – Y LAST  | CTR: HOLD MODE            |

### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 2    | Error   | Invalid Selection           |
| 5    | Error   | Too Few Data Bytes Received |

## 5.15 Command 168 Write Controller

### Request Data Bytes

| Byte | Format | Description                     |
|------|--------|---------------------------------|
| 0-31 |        | Same as Response of Command 167 |

### Response Data Bytes

| Byte | Format | Description                     |
|------|--------|---------------------------------|
| 0-31 |        | Same as Response of Command 167 |

### Command-Specific Response Codes

| Code | Class   | Description                   |
|------|---------|-------------------------------|
| 0    | Success | No Command-Specific Errors    |
| 2    | Error   | Invalid Selection             |
| 3    | Error   | Passed Parameter Too Large    |
| 4    | Error   | Passed Parameter Too Small    |
| 5    | Error   | Too Few Data Bytes Received   |
| 6    | Error   | Device-Specific Command Error |
| 16   | Error   | Access Restricted             |

### 5.16 Command 171 Read Wash

#### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
|      |        | None        |

#### Response Data Bytes

| Byte | Format | Description                         | Parameter Name on Display |
|------|--------|-------------------------------------|---------------------------|
| 0-3  | Float  | Wash Cycle [h]                      | WSH: WASH CYCLE           |
| 4-7  | Float  | Wash Time [s]                       | WSH: WASH TIME            |
| 8    | Enum   | Contact Type:<br>0 - N/O<br>1 - N/C | WSH: CONTACT              |
| 9-12 | Float  | Relax Time [s]                      | WSH: RELAX TIME           |

#### Command-Specific Response Codes

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |

### 5.17 Command 172 Write Wash

#### Request Data Bytes

| Byte | Format | Description                     |
|------|--------|---------------------------------|
| 0-12 |        | Same as Response of Command 171 |

#### Response Data Bytes

| Byte | Format | Description                     |
|------|--------|---------------------------------|
| 0-12 |        | Same as Response of Command 171 |

#### Command-Specific Response Codes

| Code | Class   | Description                   |
|------|---------|-------------------------------|
| 0    | Success | No Command-Specific Errors    |
| 2    | Error   | Invalid Selection             |
| 3    | Error   | Passed Parameter Too Large    |
| 4    | Error   | Passed Parameter Too Small    |
| 5    | Error   | Too Few Data Bytes Received   |
| 6    | Error   | Device-Specific Command Error |
| 16   | Error   | Access Restricted             |



## 5.18 Command 173 Read Clock

### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
|      |        | None        |

### Response Data Bytes

| Byte | Format      | Description  |
|------|-------------|--------------|
| 0-1  | Unsigned-16 | Milliseconds |
| 2    | Unsigned-8  | Minute       |
| 3    | Unsigned-8  | Hour         |
| 4    | Unsigned-8  | Day          |
| 5    | Unsigned-8  | Month        |
| 6    | Unsigned-8  | Year         |

### Command-Specific Response Codes

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |

## 5.19 Command 174 Write Clock

### Request Data Bytes

| Byte | Format      | Description            |
|------|-------------|------------------------|
| 0-1  | Unsigned-16 | Milliseconds (0-59999) |
| 2    | Unsigned-8  | Minute (0-59)          |
| 3    | Unsigned-8  | Hour (0-23)            |
| 4    | Unsigned-8  | Day (1-31)             |
| 5    | Unsigned-8  | Month (1-12)           |
| 6    | Unsigned-8  | Year (1-255)           |

### Response Data Bytes

| Byte | Format | Description                     |
|------|--------|---------------------------------|
| 0-6  |        | Same as Response of Command 173 |

### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 5    | Error   | Too Few Data Bytes Received |
| 9    | Error   | Invalid Date Code Detected  |
| 16   | Error   | Access Restricted           |

## 5.20 Command 175 Read Logbook Entry

### Request Data Bytes

| Byte | Format     | Description  |
|------|------------|--|
| 0    | Unsigned-8 | Group index: Value range depends on setting of Logbook options<br>No Logbook option activated: 0<br>Logbook activated: 0-49<br>Logbook + Audit Trail activated: 0-99 |

### Response Data Bytes

| Byte  | Format     | Description  |
|-------|------------|--|
| 0     | Unsigned-8 | Group Index  |
| 1     | Unsigned-8 | Index of latest entry                                  |
| 2     | Unsigned-8 | Index of the first entry of the requested group index  |
| 3-27  |            | Logbook entry  |
| 28    | Unsigned-8 | Index of the second entry of the requested group index |
| 29-53 |            | Logbook entry  |

### Logbook Entry

| Byte  | Format      | Description  |
|-------|-------------|--|
| 0     | Unsigned-8  | Message ID   |
| 1     | Unsigned-8  | Day  |
| 2     | Unsigned-8  | Month  |
| 3     | Unsigned-8  | Year   |
| 4-9   | Packed      | Time (Format: "hh:mm:ss")  |
| 10    | Bits        | Info Flags:<br>0x01 - 0x02: Sensoface<br>0 – Good<br>1 – Medium<br>2 – Bad<br>3 – Unknown<br>0x04: Parset<br>0 – ParsetA<br>1 – ParsetB<br>0x08 - 0x10: Reserved<br>0x20 - 0x80: Kind of Message<br>0 – Static<br>1 – Begin of event<br>2 – End of event<br>3 – Float (Bytes 11-14 are valid, 15-18 are reserved)<br>4 – Unsigned-32 (Bytes 15-18 are valid, 11-14 and 19-24 are reserved)<br>5 – Packed (Bytes 19-24 are valid, 11-18 are reserved) |
| 11-14 | Float       | Float Value  |
| 15-18 | Unsigned-32 | Integer Value  |
| 19-24 | Packed      | String Value   |

### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 2    | Error   | Invalid Selection           |
| 5    | Error   | Too Few Data Bytes Received |

### 5.21 Command 176 Store Actual Process Value

Command 176 takes a sample of the actual process value and stores it for later correction. This is step 1 of the product calibration.

#### Request Data Bytes

| Byte | Format | Description                                       |
|------|--------|---|
| 0    | Enum   | Sensor Selection:<br>0 – Sensor A<br>1 – Sensor B |

#### Response Data Bytes

| Byte | Format | Description                           |
|------|--------|---------------------------------------|
| 0    | Enum   | Sensor Selection (Coding see Request) |

#### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 2    | Error   | Invalid Selection           |
| 5    | Error   | Too Few Data Bytes Received |
| 16   | Error   | Access Restricted           |

### 5.22 Command 177 Read Stored Process Value

Reads the process value stored with Command 176. It returns NaN (not a number) if no value has been stored.

#### Request Data Bytes

| Byte | Format | Description                                       |
|------|--------|---|
| 0    | Enum   | Sensor Selection:<br>0 – Sensor A<br>1 – Sensor B |

#### Response Data Bytes

| Byte | Format | Description                           |
|------|--------|---------------------------------------|
| 0    | Enum   | Sensor Selection (Coding see Request) |
| 1-4  | Float  | Stored value or NaN                   |

#### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 2    | Error   | Invalid Selection           |
| 5    | Error   | Too Few Data Bytes Received |
| 16   | Error   | Access Restricted           |

### 5.23 Command 178 Write Calibration Reference Value

#### Request Data Bytes

| Byte | Format | Description                                       |
|------|--------|---|
| 0    | Enum   | Sensor Selection:<br>0 – Sensor A<br>1 – Sensor B |
| 1    | Enum   | (=0)  |
| 2-5  | Float  | Reference value                                   |

#### Response Data Bytes

| Byte | Format | Description                           |
|------|--------|---------------------------------------|
| 0    | Enum   | Sensor Selection (Coding see Request) |
| 1    | Enum   | (=0)                                  |
| 2-5  | Float  | Reference value                       |

#### Command-Specific Response Codes

| Code | Class   | Description                   |
|------|---------|-------------------------------|
| 0    | Success | No Command-Specific Errors    |
| 2    | Error   | Invalid Selection             |
| 3    | Error   | Passed Parameter Too Large    |
| 4    | Error   | Passed Parameter Too Small    |
| 5    | Error   | Too Few Data Bytes Received   |
| 6    | Error   | Device-Specific Command Error |
| 16   | Error   | Access Restricted             |

### 5.24 Command 179 Read Slope and Zero Values

#### Request Data Bytes

| Byte | Format | Description                                       |
|------|--------|---|
| 0    | Enum   | Sensor Selection:<br>0 – Sensor A<br>1 – Sensor B |

#### Response Data Bytes

| Byte | Format     | Description   |
|------|------------|---|
| 0    | Enum       | Sensor Selection (Coding see Request)   |
| 1    | Unsigned-8 | Result of the last calibration (manual or via HART), Sensoface:<br>0 – Good<br>1 – Medium<br>2 – Bad<br>3 – Unknown |
| 2    | Unsigned-8 | Slope Value Units Code (=57, %)   |
| 3-6  | Float      | Slope Value   |
| 7    | Unsigned-8 | Zero Value Units Code (=36, mV)   |
| 8-11 | Float      | Zero Value  |

#### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 2    | Error   | Invalid Selection           |
| 5    | Error   | Too Few Data Bytes Received |
| 16   | Error   | Access Restricted           |





### 5.25 Command 183 Read Device Tag

#### Request Data Bytes

| Byte | Format | Description |
|------|--------|-------------|
|      |        | None        |

#### Response Data Bytes

| Byte | Format  | Description | Parameter Name on Display |
|------|---------|-------------|---------------------------|
| 0-31 | Latin-1 | Device Tag  | TAG:                      |

#### Command-Specific Response Codes

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |

### 5.26 Command 184 Write Device Tag

#### Request Data Bytes

| Byte | Format | Description                     |
|------|--------|---------------------------------|
| 0-31 |        | Same as Response of Command 183 |

#### Response Data Bytes

| Byte | Format | Description                     |
|------|--------|---------------------------------|
| 0-31 |        | Same as Response of Command 183 |

#### Command-Specific Response Codes

| Code | Class   | Description                   |
|------|---------|-------------------------------|
| 0    | Success | No Command-Specific Errors    |
| 5    | Error   | Too Few Data Bytes Received   |
| 6    | Error   | Device-Specific Command Error |
| 16   | Error   | Access Restricted             |

## 5.27 Command 185 Read Sensor Identification

### Request Data Bytes

| Byte | Format | Description  |
|------|--------|--|
| 0    | Enum   | Info Request Selector:<br>0 – Sensor A: Sensortype<br>1 – Sensor A: Manufacturer<br>2 – Sensor A: Sensorname<br>3 – Sensor A: Serialnumber<br>4 – Sensor A: Date of last calibration<br>5 – Sensor B: Sensortype<br>6 – Sensor B: Manufacturer<br>7 – Sensor B: Sensorname<br>8 – Sensor B: Serialnumber<br>9 – Sensor B: Date of last calibration |

### Response Data Bytes

| Byte | Format  | Description   |
|------|---------|---|
| 0    | Enum    | Info Request Selector (Coding see Request)                    |
| 1    | Enum    | Sensor Connection State:<br>0 – disconnected<br>1 – connected |
| 2-17 | Latin-1 | Requested Information   |

### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 2    | Error   | Invalid Selection           |
| 5    | Error   | Too Few Data Bytes Received |

## 5.28 Command 186 Read Unit Code

### Request Data Bytes

| Byte | Format | Description                                       |
|------|--------|---|
| 0    | Enum   | Analog Channel Selection:<br>0 – OUT1<br>1 – OUT2 |

### Response Data Bytes

| Byte | Format     | Description                                   |
|------|------------|---|
| 0    | Enum       | Analog Channel Selection (Coding see Request) |
| 1    | Unsigned-8 | Units Code (Coding see 2.1)                   |

### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 2    | Error   | Invalid Selection           |
| 5    | Error   | Too Few Data Bytes Received |



## 5.29 Command 187 Read Version Info

### Request Data Bytes

| Byte | Format | Description  |
|------|--------|--|
| 0    | Enum   | Info Request Selector:<br>0 – Device: Software Version<br>1 – Device: Hardware Version<br>2 – Device: Serialnumber<br>4 – HART IF: Software Version<br>7 – Sensor A: Software Version<br>8 – Sensor A: Hardware Version<br>9 – Sensor A: Serialnumber<br>11 – Sensor B: Software Version<br>12 – Sensor B: Hardware Version<br>13 – Sensor B: Serialnumber |

### Response Data Bytes

| Byte | Format     | Description                                |
|------|------------|--|
| 0    | Unsigned-8 | Info Request Selector (Coding see Request) |
| 1-16 | Latin-1    | Requested Information                      |

### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 2    | Error   | Invalid Selection           |
| 5    | Error   | Too Few Data Bytes Received |

## 5.30 Command 188 Read Calibration Values

### Request Data Bytes

| Byte | Format     | Description  |
|------|------------|--|
| 0    | Unsigned-8 | Info Request Selector:<br>0 – Sensor A: Zero [mV]<br>1 – Sensor A: Slope [%]<br>2 – Sensor A: ISFET Offset [mV]<br>3 – Sensor A: Time of next calibration [h]<br>4 – Sensor B: Zero [mV]<br>5 – Sensor B: Slope [%]<br>6 – Sensor B: ISFET Offset [mV]<br>7 – Sensor B: Time of next calibration [h]<br>8 – Sensor A: Delta ORP [mV]<br>9 – Sensor B: Delta ORP [mV] |

### Response Data Bytes

| Byte | Format     | Description                                      |
|------|------------|--|
| 0    | Unsigned-8 | Info Request Selector (Coding see Request)       |
| 1    | Enum       | Unit Codes:<br>0x24 – mV<br>0x57 – %<br>0x52 – h |
| 2-5  | Float      | Calibration Value                                |

### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 2    | Error   | Invalid Selection           |
| 5    | Error   | Too Few Data Bytes Received |



### 5.31 Command 189 Read Process Values

#### Request Data Bytes

| Byte | Format     | Description   |
|------|------------|---|
| 0    | Unsigned-8 | Info Request Selector:<br>0 – Sensor A: Temperature<br>1 – Sensor A: Impedance of glass electrode [kOhm]<br>2 – Sensor A: pH value [pH]<br>3 – Sensor A: Glass mV value (pH) [mV]<br>4 – Sensor B: Temperature<br>5 – Sensor B: Impedance of glass electrode [kOhm]<br>6 – Sensor B: pH value [pH]<br>7 – Sensor B: Glass mV value (pH) [mV]<br>8 – Current input value [mA]<br>9 – Sensor A: ORP value [mV]<br>10 – Sensor A: Glass-mV value (ORP) [mV]<br>11 – Sensor B: ORP value [mV]<br>12 – Sensor B: Glass-mV value (ORP) [mV] |

#### Response Data Bytes

| Byte | Format     | Description   |
|------|------------|---|
| 0    | Unsigned-8 | Info Request Selector (Coding see Request)  |
| 1    | Enum       | Unit Codes:<br>0x20 – °C<br>0x21 – °F<br>0x24 – mV<br>0x25 – Ohm<br>0x27 – mA<br>0x3B – pH<br>0xA3 – kOhm |
| 2-5  | Float      | Process Value   |

#### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 2    | Error   | Invalid Selection           |
| 5    | Error   | Too Few Data Bytes Received |

### 5.32 Command 190 Read Digital Sensor Information

#### Request Data Bytes

| Byte | Format     | Description   |
|------|------------|---|
| 0    | Unsigned-8 | Value Request Selector:<br>0 – Sensor A: Operation time<br>1 – Sensor A: Sensor wear<br>2 – Sensor A: Lifetime<br>3 – Sensor B: Operation time<br>4 – Sensor B: Sensor wear<br>5 – Sensor B: Lifetime |

#### Response Data Bytes

| Byte | Format     | Description                                     |
|------|------------|---|
| 0    | Unsigned-8 | Value Request Selector (Coding see Request)     |
| 1    | Enum       | Unit Codes:<br>0x35 – d<br>0x34 – h<br>0x39 – % |
| 2-5  | Float      | Requested value                                 |

#### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 2    | Error   | Invalid Selection           |
| 5    | Error   | Too Few Data Bytes Received |

### 5.33 Command 191 Read Last Calibration Date

#### Request Data Bytes

| Byte | Format | Description                                       |
|------|--------|---|
| 0    | Enum   | Sensor Selection:<br>0 – Sensor A<br>1 – Sensor B |

#### Response Data Bytes

| Byte | Format  | Description                                    |
|------|---------|--|
| 0    | Enum    | Sensor Selection (Coding see Request)          |
| 1-8  | Latin-1 | Date of latest calibration (Format „dd.mm.yy“) |

#### Command-Specific Response Codes

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |

### 5.34 Command 192 Read User Specific Buffer Values

#### Request Data Bytes

| Byte | Format     | Description   |
|------|------------|---|
| 0    | Unsigned-8 | Groupindex:<br>Sensor A:<br>0 – Buffer 1 at 0°C to 45°C [pH] (at 25°C = nominal value of buffer 1)<br>1 – Buffer 1 at 50°C to 95°C [pH]<br>2 – Buffer 2 at 0°C to 45°C [pH] (at 25°C = nominal value of buffer 2)<br>3 – Buffer 2 at 50°C to 95°C [pH]<br>Sensor B:<br>4 – Buffer 1 at 0°C to 45°C [pH] (at 25°C = nominal value of buffer 1)<br>5 – Buffer 1 at 50°C to 95°C [pH]<br>6 – Buffer 2 at 0°C to 45°C [pH] (at 25°C = nominal value of buffer 2)<br>7 – Buffer 2 at 50°C to 95°C [pH] |

#### Response Data Bytes

| Byte | Format      | Description  |
|------|-------------|--|
| 0    | Unsigned-8  | Groupindex (Coding see Request)  |
| 1-40 | Float array | 10 buffer values of the group requested by groupindex. The one for the lowest temperature value of the group is transmitted first. |

#### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 2    | Error   | Invalid Selection           |
| 5    | Error   | Too Few Data Bytes Received |

### 5.35 Command 193 Write User Specific Buffer Values

#### Request Data Bytes

| Byte | Format | Description                     |
|------|--------|---------------------------------|
| 0-40 |        | Same as Response of Command 192 |

#### Response Data Bytes

| Byte | Format | Description                     |
|------|--------|---------------------------------|
| 0-40 |        | Same as Response of Command 192 |

#### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 2    | Error   | Invalid Selection           |
| 5    | Error   | Too Few Data Bytes Received |

### 5.36 Command 194 Read User Specific Buffer Set Consistency Check Result

#### Request Data Bytes

| Byte | Format | Description                                       |
|------|--------|---|
| 0    | Enum   | Sensor Selection:<br>0 – Sensor A<br>1 – Sensor B |

#### Response Data Bytes

| Byte | Format | Description   |
|------|--------|---|
| 0    | Enum   | Sensor Selection (Coding see Request)   |
| 1    | Enum   | Result of user buffer set consistency check:<br>0 – ok<br>1 – not ok (data is inconsistent) |

#### Command-Specific Response Codes

| Code | Class   | Description                |
|------|---------|----------------------------|
| 0    | Success | No Command-Specific Errors |

### 5.37 Command 195 Write TV and QV Assignment

#### Request Data Bytes

| Byte | Format     | Description   |
|------|------------|---|
| 0    | Unsigned-8 | Device Variable assigned to the Tertiary Variable   |
| 1    | Unsigned-8 | Device Variable assigned to the Quaternary Variable |

#### Response Data Bytes

| Byte | Format     | Description   |
|------|------------|---|
| 0    | Unsigned-8 | Device Variable assigned to the Tertiary Variable   |
| 1    | Unsigned-8 | Device Variable assigned to the Quaternary Variable |

#### Command-Specific Response Codes

| Code | Class   | Description                 |
|------|---------|-----------------------------|
| 0    | Success | No Command-Specific Errors  |
| 2    | Error   | Invalid Selection           |
| 5    | Error   | Too Few Data Bytes Received |
| 16   | Error   | Access Restricted           |

### 5.38 Command 196 Read Product Calibration Success

#### Request Data Bytes

| Byte | Format | Description                                       |
|------|--------|---|
| 0    | Enum   | Sensor Selection:<br>0 – Sensor A<br>1 – Sensor B |

#### Response Data Bytes

| Byte | Format     | Description  |
|------|------------|--|
| 0    | Enum       | Sensor Selection (Coding see Request)  |
| 1    | Unsigned-8 | Result of Latest Product Calibration done via HART<br>0 – Success<br>1 – Fail<br>2 – Busy (result not yet available) |

#### Command-Specific Response Codes

| <b>Code</b> | <b>Class</b> | <b>Description</b>          |
|-------------|--------------|-----------------------------|
| 0           | Success      | No Command-Specific Errors  |
| 2           | Error        | Invalid Selection           |
| 5           | Error        | Too Few Data Bytes Received |